

TESTATUT HIMMENTIMET

	SÄHKÖNUMEROT	LINDER 8W	LINDER 16W	CONE 9W	TINKA 7W	TINKA 15W	SPIKE 4W	DONUT 25W	FRISBEE 18W	PEARL SINGLE	PEARL CLUSTER	PEARL LINE
Schneider Electric Valonsäädin 9-100VA RL	26 222 04 (Exact)	—	—	—	—	—	—	—	✓	—	—	—
Schneider Electric LED-Valonsäädin 4-400VA RCL	26 222 25 (Exact)	✓	✓	—	✓	✓	✓	✓	✓	✓	✓	—
Schneider Electric Valonsäädin 420VA RCL	26 221 81 (Exact) 35 124 45 (Arctic)	✓	—	—	—	—	✓	✓	✓	✓	—	✓
Schneider Electric Valonsäädin 40-315VA RC	26 221 61 (Exact) 35 124 39 (Arctic)	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
ABB LED-valonsäädin 2-100VA RL	26 193 45 (Impressivo) 26 193 44 (Jussi)	✓	✓	—	✓	✓	✓	✓	✓	✓	✓	✓
ABB Valonsäädin 40-420VA RCL	35 127 51 (Impressivo) 26 200 24 (Jussi)	—	✓	—	—	✓	—	✓	✓	—	✓	—
ABB Valonsäädin 40-420VA RC	26 193 27 (Impressivo) 35 127 85 (Jussi)	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
ABB Valonsäädin 20-500VA RL	35 127 13 (Impressivo) 35 127 50 (Jussi)	✓	—	✓	✓	✓	✓	✓	✓	✓	—	—
ABB Painikesäädin 2-100VA RCL	26 193 47	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
ABB Painikesäädin 40-315VA RC	35 127 93 (Impressivo) 35 127 92 (Jussi)	—	✓	✓	✓	✓	—	✓	✓	✓	✓	✓
Elko Valonsäädin 40-315VA GLE RC	35 140 66	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
Elko Painikesäädin 20-400VA GLE/RL RC	35 139 80	✓	✓	—	—	✓	—	✓	—	—	✓	✓
Schneider Uppoasennettava LED-painikesäädin 5-200VA	26 091 11	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—
ABB Langaton säädin 35-210VA RCL	Painike: 2815256 Vastaanotin: 2815266	—	✓	✓	—	—	—	—	✓	—	✓	—
Schneider Electric Connect langaton RCL 25-250VA	Painike: 2622271 Vastaanotin: 3575741	—	✓	✓	—	—	✓	✓	✓	✓	—	—
ABB Painikesäädin 2-100VA RCL LED "Keskus"	26 193 72	—	✓	✓	✓	✓	—	—	—	✓	✓	—